

## DG Model 200 kVA



Product photos are only for representation purpose

### GENSET PARAMETERS

kVA (Prime)	200
kW (Prime)	160
Engine Make & Model	Mahindra mPower (mPower62485G)
Alternator Make	Leroy Somer
Phase	3- Phase
Voltage	415 V, 3-Phase
Frequency / Engine Speed	50 Hz / 1500 rpm
Rated Current (A)	278 (3-Phase)
Power Factor (p.f.)	0.8 (Lag)
Fuel Tank Capacity (Litre)	400
Noise Level	Genset with acoustic enclosure shall have average noise level of 75dBA at 1 meters distance as per stringent guidelines of Central Pollution Control Board, India
Conformance to Standards	ISO 8528

### ENGINE PARAMETERS

Model	mPower62485G
Make	Mahindra mPower
Rated Engine power @100% Load (HP)	248
Cylinders	6
Aspiration	TCA
Displacement in CC	72
Bore x Stroke in mm	105 x 137
Governing System	G2 as per ISO 8528 Part V
Total Lube Oil System Capacity in Litre	20.2
Radiator Coolant Capacity in Litre	24
Fuel	High Speed Diesel
Lube Oil Specification	15W40 API CI4+
Starting System (V)	24V DC Electrical
Cooling System	Water cooled with Radiator

### FUEL CONSUMPTION

Fuel Consumption @ 100 % Load (Prime)	40.8 Ltr./hr.
Fuel Consumption @ 75 % Load (Prime)	33.3 Ltr./hr.

### LOGISTIC DATA

Dimensions (L x W x H) in mm	Silent Set : 4300 x 1400 x 1800
Approx. Net wet in Kg.	Silent Set :2800

### ALTERNATOR PARAMETERS

Make	Leroy Somer
Type	Brushless, Single Bearing, Self Excited
Voltage	415 V (3-phase)
Phase	3 phase
Frequency	50 Hz
Speed	1500 RPM
Voltage Regulation	+/- 1%
Insulation class	H
Ingress Protection	IP 23

### CONTROL PANEL PARAMETERS

Control Panel Type	Manual control Panel with microprocessor based controller (Standard)/ AMF (optional)
Controller Make & Type	Deep Sea Controller (4521/7320)
Protection Features offered by controller	Engine - High Water Temperature, Low Lube oil pressure, Low Fuel Level Electrical - Generator Under/Over Voltage, Generator Under/Over Frequency, Generator Over Current, Generator kW Overload

Note: Technical specifications are subjected to change without prior notice